U?

GL865_V3

<Value>

Pin	Name
1	C109/DCD/GPO
2	C125/RING/GPO
3	C107/DSR/GPO
4	C108/DTR/GPI
5	C105/RTS/GPI
6	C106/CTS/GPO
7	C103/TXD
8	C104/RXD
9	SIMVCC
10	SIMRST
11	SIMCLK
12	SIMIO

Top pins:
Pin	Name
48	RESERVED
47	RESET*
46	GND_4
45	TXD_AUX
44	RXD_AUX
43	V_AUX/PWRMON
42	GPIO_01/DVI_WA0
41	GPIO_02/JDR/DVI_RX
40	GPIO_03/DVI_TX
39	GPIO_04/TX Disable/DVI_CLK
38	VBATT
37	VBATT_PA

Bottom pins:
Pin	Name
13	ADC_IN1
14	ADC_IN2
15	DAC_OUT
16	RESERVED_1
17	RESERVED_2
18	RESERVED_3
19	RESERVED_4
20	
21	EAR-
22	EAR+
23	MIC-
24	AGND
	MIC+

Right pins:
Pin	Name
36	GND_3
35	GND_2
34	ANTENNA
33	GND_1
32	GND
31	RESERVED_6
30	VRTC
29	GPIO_05/RFTXMON
28	GPIO_06/ALARM
27	GPIO_07/BUZZER
26	GPIO_08/STAT_LED
25	RESERVED_5